

WR 2000A

2-Channel Rework Station Set, 200 W (300 W)

Product no.: T0053378699N



Benefits

- › Hot air station WR 2, 2 channels with hot air iron HAP 1
- › Small hot air set
- › Simultaneous operation of 2 soldering tools
- › All soldering tools upto 200 W connectable



Technical Data

Dimensions L x W x H (mm)	280 x 240 x 103
Dimensions L x W x H (inches)	11,02 x 9,45 x 4,06
Weight (approx.) in kg	5.6
Voltage	230 V
Power	250 W (300 W)
Channels	2
Temperature range (depends on tool) °C	50 - 550
Temperature range (depends on tool) °F	150 - 950
Temperature accuracy °C	±9
Temperature accuracy °F	±17
Temperature stability °C	±2
Temperature stability °F	±4
Equipotential bonding socket	Via a 3.5 mm jack bush (initial state-hard-grounded).
Display	LCD
Air consumption l/min	---
Operating pressure in bar/psi	---
Capacity l/min	18
Vacuum	0,7 bar